

DUAL Cloud dual Hub:

```
R1-Hub1
int e0/0
Desc conn to internet
ip add 1.1.1.1 255.255.255.0
no sh
int e0/1
ip add 10.1.1.1 255.255.255.0
no sh
exit
ip route 0.0.0.0 0.0.0.0 1.1.1.4
```

```
interface Tunnel1
ip address 192.168.1.1 255.255.255.0
ip nhrp authentication dmvpn123
ip nhrp map multicast dynamic
ip nhrp network-id 123
ip nhrp redirect
tunnel source Ethernet0/0
tunnel mode gre multipoint
tunnel key 123
end
```

```
Router eigrp 1
net 192.168.1.0
net 10.0.0.0
passive-interface e0/0
exit
```

```
R4-Hub2
int e0/0
Desc conn to internet
ip add 4.4.4.4 255.255.255.0
no sh
int e0/1
ip add 10.1.1.4 255.255.255.0
no sh
exit
ip route 0.0.0.0 0.0.0.0 4.4.4.1
```

```
interface Tunnel2
ip address 192.168.2.4 255.255.255.0
ip nhrp authentication dmvpn423
ip nhrp map multicast dynamic
ip nhrp network-id 423
ip nhrp redirect
tunnel source Ethernet0/0
tunnel mode gre multipoint
tunnel key 423
end
```

```
Router eigrp 1
net 192.168.2.0
net 10.0.0.0
```

```
passive-interface e0/0
```

```
exit
```

```
Spoke-1
```

```
interface Tunnel1
```

```
ip address 192.168.1.2 255.255.255.0
```

```
no ip redirects
```

```
ip nhrp authentication dmvpn123
```

```
ip nhrp network-id 123
```

```
ip nhrp nhs 192.168.1.1 nbma 1.1.1.1 multicast
```

```
ip nhrp shortcut
```

```
tunnel source Ethernet0/0
```

```
tunnel mode gre multipoint
```

```
tunnel key 123
```

```
end
```

```
interface Tunnel2
```

```
ip address 192.168.2.2 255.255.255.0
```

```
no ip redirects
```

```
ip nhrp authentication dmvpn423
```

```
ip nhrp network-id 423
```

```
ip nhrp nhs 192.168.2.4 nbma 4.4.4.4 multicast
```

```
ip nhrp shortcut
```

```
tunnel source Ethernet0/0
```

```
tunnel mode gre multipoint
```

```
tunnel key 423
```

```
end
```

```
Router eigrp 1
```

```
net 192.168.1.0
```

```
net 192.168.2.0
```

```
net 10.0.0.0
```

```
exit
```

```
Spoke-2
```

```
interface Tunnel1
```

```
ip address 192.168.1.3 255.255.255.0
```

```
ip nhrp authentication dmvpn123
```

```
ip nhrp network-id 123
```

```
ip nhrp nhs 192.168.1.1 nbma 1.1.1.1 multicast
```

```
ip nhrp shortcut
```

```
tunnel source Ethernet0/0
```

```
tunnel mode gre multipoint
```

```
tunnel key 123
```

```
end
```

```
interface Tunnel2
```

```
ip address 192.168.2.3 255.255.255.0
```

```
ip nhrp authentication dmvpn423
```

```
ip nhrp network-id 423
```

```
ip nhrp nhs 192.168.2.4 nbma 4.4.4.4 multicast
```

```
ip nhrp shortcut
```

```
ip nhrp hold 100
```

```
tunnel source Ethernet0/0
```

```
tunnel mode gre multipoint  
tunnel key 423  
end
```

```
Router eigrp 1  
net 192.168.1.0  
net 192.168.2.0  
net 10.0.0.0  
exit
```